

commodoreCOMMODORE BUSINESS MACHINES, INC.
3330 SCOTT BOULEVARD
SANTA CLARA, CALIFORNIA 95050
TELEPHONE: (408) 727-1130 TELEX: 171141
CABLE ADDRESS COMBUSMAC

8K MAIN LOGIC ASSEMBLY PARTS CROSS REFERENCE

<u>REF. DES.</u>	<u>DESCRIPTION</u>	<u>PART NO.</u>	<u>DEALER PRICE</u>
1. C1,C2,C14	.01MF 100V Ceramic	900010-38	\$.06
2. C3	82PF 500V Ceramic	900010-40	.09
3. C4	10PF 500V Ceramic	900010-35	.09
4. C5,C11,C12,C13	1.0MF 25V Tantalum	900402-13	.28
5. C6	.1MF 50V Ceramic	900010-20	.14
6. C7-C10	47MF 16V Electrolytic	900100-33	.13
7. C15-C49	.1MF 10V Ceramic	900010-39	.13
8. CR1,CR2,CR3	IN5402 3A/200V	900753-01	.28
9. DSI	LED Indicator	900701-01	.26
10. J5	20 Pin Header (Molex)	903307-02	.79
11. J7	7 Pin Header (Molex)	903307-03	.31
12. J8	5 Pin Header (Molex)	903302-02	.40
13. Q1,Q4	TIP 29	902653-01	.51
14. Q2,Q5	2N 4401	902652-01	.15
15. Q3,Q6	2N 3904	902658-01	.14
16. R1,R4	1.5K 1/4W 5%	901550-69	.05
17. R2,R6,R12,R13,R14	10K 1/4W 5%	901550-20	.05
18. R18-R25	10K 1/4W 5%	901550-20	.05
19. R3,R5,R26-R46	1K 1/4W 5%	901550-01	.05
20. R7,R8,R9	470 1/4W 5%	901550-58	.05
21. R10	2.4K 1/4W 5%	901550-85	.05
22. R11	5.1K 1/4W 5%	901550-03	.05

commodore



COMMODORE BUSINESS MACHINES, INC.
3330 SCOTT BOULEVARD
SANTA CLARA, CALIFORNIA 95050
TELEPHONE: (408) 727-1130 TELEX: 171141
CABLE ADDRESS COMBUSMAC

<u>REF. DES.</u>	<u>DESCRIPTION</u>	<u>PART NO.</u>	<u>DEALER PRICE</u>
23. R15,R16	IM 1/4W 5%	901550-84	.05
24. R17	3.3K 1/4W 5%	901550-02	.05
25. UAI,UB5,UC9	74LS93 Counter	901521-07	.60
26. UA2	6540-010 MOS Char. Gen.	901439-08	20.00
27. UA2	2316B-08 Char. Gen.	901447-08	20.00
28. UA5	6522 VIA	901437-01	20.00
29. UA7,UA8,UA9	MC 3446 Interface Bus.	901524-01	2.47
30.UBI,UE8,UE9	74LS20 Nand Gate	901521-04	.30
31.UB2	74LS165 Shift Reg.	901521-12	.39
32.UB3,UB4,UG5, UG6,UH8,UH9	74LS244 Buffer	901521-13	1.64
33. UB6,UC5,UC7, UC8,UD5	74LS107 Flip-Flop	901521-08	.49
34. UB8,UG8	6520 PIA	901436-01	20.00
35. UCI	74LS 74 Flip-Flop	901521-06	.50
36. UC2,UD8,UG3	74LS 00 Nand Gate	901521-01	.33
37. UC3,UC4,U11-U18, UJ1-UJ8	6550 RAM	901438-01	12.00
38. UC3,UC4,U11-U18, UJ1-UJ8	2114 RAM	901453-01	12.00
39. UC6,UE2	74LS08	901521-03	.31
40. UD2,UD3,UD4	74LS157 Data Sel	901521-11	.73
41. UD6,UD7	74177 Counter	901522-03	1.00
42. UD9,UE5	74LS04 Hex Inv	901521-02	.35
43. UDE9	LM555 Timer	901523-01	.45
44. UE3,UE4	7417 Hex Buffer	901522-01	.40
45. UE6	74100 Latch	901522-02	1.00

commodore



COMMODORE BUSINESS MACHINES, INC.
3330 SCOTT BOULEVARD
SANTA CLARA, CALIFORNIA 95050
TELEPHONE: (408) 727-1130 TELEX: 171141
CABLE ADDRESS COMBUSMAC

<u>REF. DES.</u>	<u>DESCRIPTION</u>	<u>PART NO.</u>	<u>DEALER PRICE</u>
46. UF3	6502 MPU	901435-01	11.25
47. UG2	74LS154 Decoder	901521-10	1.10
48. UG4	74LS21 And Gate	901521-05	.73
49. UG9	74LS145	901521-09	1.10
50. UHI	6540-019 ROM	901439-09	20.00
51. UHI	2316B-09 ROM	901447-09	20.00
52. UH2	6540-013 ROM	901439-02	20.00
53. UH2	2316B-03 ROM	901447-03	20.00
54. UH3	6540-015 ROM	901439-03	20.00
55. UH3	2316-B-05 ROM	901447-05	20.00
56. UH4	6540-016 ROM	901439-04	20.00
57. UH4	2316B-06 ROM	901447-06	20.00
58. UH5	6540-012 ROM	901439-05	20.00
59. UH5	2316B-02 ROM	901447-02	20.00
60. UH6	6540-014 ROM	901439-06	20.00
61. UH6	2316B-04 ROM	901446-04	20.00
62. UH7	6540-018 ROM	901439-07	20.00
63. UH7	2316B-07 ROM	901446-07	20.00
64. UA2,UH1-UH7	Socket 28 PIN	904150-05	.50
65. UA2,UH1-UH7	Socket 24 PIN	904150-04	.34
66. UA5,UB8,UF3,UG8	Socket 40 PIN	904150-06	.56
67. UC3,UC4,UJ1-UJ8, U11-U18	Socket 22 PIN	904150-03	.41